

Karolina Cicha Solo

Technical Rider

FOH Mixer & Outboard

A digital mixer, 16 mono channels + 4 stereo; each channel should be equipped with a parametric 4-point EQ, a sweepable HP filter, phase switch, Phantom Power 48V, 5x AUX Post; a small lamp.

Preferred desk types: Avid Venue, Soundcraft Vi, M32 (full version).

If an analog mixer is to be used it should be accompanied with the following outboard:

- dynamic processors according to the input list
- two high quality reverb processors
- one tap-delay
- stereo graphic EQ

A grounded 230V “schuko” power source for additional equipment.

The subwoofer source preferably from AUX Post.

The sound engineer should be able to communicate with the artist during the soundcheck – a switchable microphone connected to the monitoring system is expected.

Monitoring

One 12” 200W RMS floor wedge monitor and one high quality IEM system.

If the monitoring is to be conducted from the main mixer it should be equipped with 2 additional AUX Pre sends with GEQ for every send and a monitoring speaker.

Stage

One straight chair without armrests, one small table (50x50x50 cm). Two boom mic stands.

Grounded 230V “schuko” power source.

XLR Y splitter for vocal mic (XLR F -> 2x XLR M).

We need at least 60 minutes for setup and soundcheck.

Please contact the band’s sound engineer in advance.

Karolina Cicha Solo

Stage Plan

1

(1-10)

Input list				
Channel	Source	Mic/line	Insert	Stage position
1	Roland SPD L	DiBox/Thru		1
2	Roland SPD R	DiBox/Thru		1
3	Piano L	DiBox	comp	1
4	Piano R	DiBox	comp	1
5	Helicon L (v)	XLR	comp	1
6	Helicon R (g)	XLR		1
7	Accordion R	DiBox		1
8	Accordion L	DiBox		1
9	OH	e914		1
10	Voc	SM58 (XLR Y)	comp	1
St. Ret. 1	Reverb room			
St. Ret. 2	Reverb hall			
St. Ret. 3	Tap delay			
St. Ret. 4	Engineer's FX			
Microphone models are given as an example, similar models might be used. Use only high quality DI boxes, please! No wireless mics, please!				

Monitoring & Stage setup			
Stage position	Aux line	Monitor type	Notes
1	Send Pre 1	Floor wedge	Power 230V (Schuko)
1	Send Pre 2	IEM	